



## **BSL36B18X**

MULTI VOLT Battery 36/18V - 4.0/8.0 Ah

Powers 18V and 36V tools

**High power output** 

Improved water and drop resistance



| Specifications              |                  |
|-----------------------------|------------------|
| Voltage                     | 36/18V           |
| Capacity                    | 4.0/8.0 Ah       |
| Energy                      | 2x 72 Wh         |
| Battery level indicator     | $\checkmark$     |
| Charging time with UC18YSL3 | 52 min.          |
| Charging time with UC18YFSL | 120 min.         |
| Numbers of cells            | 10               |
| Cell size (Ø x L)           | 21 x 70 mm       |
| Dimensions (L x W x H)      | 134 x 83 x 77 mm |
| Weight <sup>1</sup>         | 1,020 g          |

## Characteristics

Automatic Switching System - Intelligent circuitry changes voltage automatically to power all 18V and 36V HiKOKI tools

36 V nominal voltage and up to 41 V after charging allowing the batteries to deliver the power to increase productivity and efficiency

Intelligent electronics ensures constant communication between tool, battery and charger to prevent overload, overheating, overcharge and overdischarge for longest battery and tool life

Improved water resistance and drain outlets for prolonged lifetime

15% improved shock resistance via dual-layer elastomer base guarding against drops and surface damage

Integrated 4-LED display shows remaining battery charge to prevent costly downtime on the job

21,700 cells offer greater capacity and higher discharge capability Higher power output achievable than with similar sized 18V batteries

## Versions<sup>2</sup>

 380084:
 1x MULTI VOLT BSL36B18X battery,

 00000000000
 cardboard box

 380207:
 2x MULTI VOLT BSL36B18X battery,

 000000000000
 cardboard box

 UC18YSL3WJZ:
 2x MULTI VOLT BSL36B18X battery,

 000000000000
 fastcharger UC18YSL3, cardboard box

Read everything about our services at **hikoki-powertools.eu** 



<sup>&</sup>lt;sup>1</sup>Weight according to EPTA-2004 procedure.

<sup>&</sup>lt;sup>2</sup> Standard accessories vary by country or area.